


PA8

Taps and splitters



8-output vertical splitter with F connector for TV and Satellite band (5-2400MHz).

Technical Chars

- The design and the small dimensions allow the installation in any wall box.
- **Die-cast and nickel-plated**, they ensure high performance, with very low insertion loss, high return loss and insulation.
- Built-in earth bounding screw and wall-mount fixings.
- **DC pass-through between outputs to input.**

PA8		
Code		280705
Outputs		8
Insertion loss		
RC 5-40MHz	dB	12
TV 47-862MHz	dB	12.5
SAT 950-1750MHz	dB	15.5
SAT 1750-2150MHz	dB	16.5
SAT 2150-2400MHz	dB	17
Outputs Isolation		
RC 5-40MHz	dB	20
TV 47-862MHz	dB	20
SAT 950-1750MHz	dB	20
SAT 1750-2150MHz	dB	20
SAT 2150-2400MHz	dB	20
Dimensions and packaging		
Pieces		10
EAN code		8016978034833
Multiple EAN		8016978035038
Packaging dimensions	mm	310 x 125 x 50
Packaging weight	Kg	1.37